

MASTR[®]II MAINTENANCE MANUAL

138-174 MHz, 110-WATT TRANSMITTER - MOBILE AND STATION




TABLE OF CONTENTS

SPECIFICATIONS	ii
DESCRIPTION AND MAINTENANCE	LBI30738 (DF3156)
EXCITER	LBI30422 (DF3165)
POWER AMPLIFIER	LBI307 39 (DF3166)

SPECIFICATIONS*

Power Output

Crystal Multiplication Factor

Frequency Stability:

5C-ICOM with EC-ICOM

2C-ICOMS

Spurious and Harmonic Emission (Per EIA RS-152-B, Para. 4)

Modulation

Audio Sensitivity

Audio Frequency Characteristics

Distortion

Deviation Symmetry

Maximum Frequency Spread:

138-155 MHz 150.8-174 MHz

Duty Cycle

RF Output Impedance

Temperature Range:

110 Watts (Adjustable from 22 to 110 Watts)

12

 $\pm 0.0005\%$

 $\pm 0.0002\%$

At least 85 dB below full rated power output.

Adjustable from 0 to ± 5 kHz swing with instantaneous modulation limiting.

75 to 120 Millivolts (Mobile) 10 to 120 Millivolts (Station)

Within +1 dB to -3 dB of a 6-dB/octave pre-emphasis from 300 to 3000 Hz per EIA standards. Post limiter filter per FCC and EIA.

Less than 2% (1000 Hz) Less than 3% (300 to 3000 Hz)

0.5 kHz maximum

Full 1 dB
Specifications Degradation
1.8 MHz 2.75 MHz
2.0 MHz 3.0 MHz

EIA 20% Intermittent (Mobile & Station) Continuous (Station)

50 ohms

-40 °C to +70 °C (Mobile) -30 °C to +60 °C (Station)

*These specifications are intended primarily for the use of the serviceman. Refer to the appropriate Specification Sheet for the complete specifications.

- WARNING -

Although the highest DC voltage supplied to the MASTR II transmitter is 12 Volts DC, high currents may be drawn under short circuit conditions. These currents can possibly heat metal objects such as tools, rings, watchbands, etc., enough to cause burns. Be careful when working near energized circuits!

High-level RF energy in the transmitter Power Amplifier assembly can cause RF burns upon contact. KEEP AWAY FROM THESE CIRCUITS WHEN THE TRANSMITTER IS ENERGIZED!

GENERAL ELECTRIC COMPANY • MOBILE COMMUNICATIONS DIVISION WORLD HEADQUARTERS • LYNCHBURG, VIRGINIA 24502 U.S.A.

