

IFR 500/500A Electrolytic Capacitor Parts List

By: Alex, KD6VPH

Preface: This guide was put together to aid in renewal of the electrolytic capacitors in your IFR 500/500A. This guide should not be interpreted as stating that all the electrolytic capacitors in your 500/500A need renewal. During the renewal process it is very important to clean and remove any boric acid that may have leaked out- use a Q-tip and 90% Isopropyl Alcohol. Electrolytic capacitor replacement is easily accomplished using a de-soldering station such as a Hakko 472D, JBC 1D, Weller WR3000, etc. but not absolutely necessary.

Power Supply PC Board Assembly

C7, C9, C12, C20- 10uF, 50V, 20%, Radial Lead, 85 deg

Replacement Manufacturer: Panasonic

Replacement Part Number: ECE-A1HKS100B

Digikey Part Number: P19588CT-ND

Quantity in Assembly: 4

C5 - 47uF, 10V, 20%, Radial Lead, 105 deg

Replacement Manufacturer: Nichicon

Replacement Part Number: UMF1A470MDD1TP

Digikey Part Number: 493-10218-1-ND

Quantity in Assembly: 1

OR

C5 - 47uF, 10V, 20%, Radial Lead, 85 deg

Replacement Manufacturer: Nichicon

Replacement Part Number: UMA1A470MDD1TP

Digikey Part Number: 493-10439-1-ND

Quantity in Assembly: 1

C1, C2 -100uF, 50v, 20%, Radial Lead, 85 deg

Replacement Manufacturer: Nichicon

Replacement Part Number: UVK1H101MDD1TD

Digikey Part Number: 493-12570-1-ND

Quantity in Assembly: 2

C8 -470uF, 35V, 20%, Axial Lead, 85 deg

Replacement Manufacturer: Nichicon

Replacement Part Number: TVX1V471MCD

Digikey Part Number: 493-13379-ND

Quantity in Assembly: 1

C19 - 330uF, 16V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Vishay
Replacement Part Number: MAL202135331E3
Digikey Part Number: 4020PHCT-ND
Quantity in Assembly: 1

C6 -10000uF, 10V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1A103MCD
Digikey Part Number: 493-14803-ND
Quantity in Assembly: 1

C3 -4700uF, 25V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1E472MCD
Digikey Part Number: 493-14406-ND
Quantity in Assembly: 1

Frequency Standard PC Board

C9 - 47uF, 25V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1E470MAD
Digikey Part Number: 493-14405-ND
Quantity in Assembly: 1

Generate Audio PC Board

C3 - 1uF, 50V, 20%, Radial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: URS1H010MDD1TD
Digikey Part Number: 493-11473-1-ND
Quantity in Assembly: 1

C5, C8, C13 - 10uF, 35V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1V100MAD
Digikey Part Number: 493-14419-ND
Quantity in Assembly: 3

C1, C19 - 330uF, 16V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Vishay
Replacement Part Number: MAL202135331E3
Digikey Part Number: 4020PHCT-ND
Quantity in Assembly: 2

Receive Audio PC Board

C, C, C - 1uF, 50V, 20%, Radial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: URS1H010MDD1TD
Digikey Part Number: 493-11473-1-ND
Quantity in Assembly: 3

C, C, C – 3.3uF, 50V, 20%, Radial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: URS1H3R3MDD1TD
Digikey Part Number: 493-11476-1-ND
Quantity in Assembly: 3

C, C - 10uF, 35V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1V100MAD
Digikey Part Number: 493-14419-ND
Quantity in Assembly: 2

Variable Tone Generator PC Board

C32, C34 - 10uF, 35V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1V100MAD
Digikey Part Number: 493-14419-ND
Quantity in Assembly: 2

C4, C33, C37 -47uF, 10V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1A470MAD
Digikey Part Number: 493-14808-ND
Quantity in Assembly: 3

Digital Counter and Digital Reference PC Boards

***13 Pin Header, Double Decker Boards ***

Digital Counter PC Board

C9, C20 – 3.3uF, 50V, 20%, Radial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: URS1H3R3MDD1TD
Digikey Part Number: 493-11476-1-ND
Quantity in Assembly: 2

Digital Reference PC Board

C31, C34 - 10uF, 50V, 20%, Radial Lead, 85 deg
Replacement Manufacturer: Panasonic
Replacement Part Number: ECE-A1HKS100B
Digikey Part Number: P19588CT-ND
Quantity in Assembly: 2

C1, C3 - 10uF, 35V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1V100MAD
Digikey Part Number: 493-14419-ND
Quantity in Assembly: 2

C11 -47uF, 10V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1A470MAD
Digikey Part Number: 493-14808-ND
Quantity in Assembly: 1

Receiver/Generator PC Board

C - 10uF, 50V, 20%, Radial Lead, 85 deg
Replacement Manufacturer: Panasonic
Replacement Part Number: ECE-A1HKS100B
Digikey Part Number: P19588CT-ND
Quantity in Assembly: 1

C32 -47uF, 10V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1A470MAD
Digikey Part Number: 493-14808-ND
Quantity in Assembly: 1

Low Loop PC Board

C26 - 1uF, 50V, 20%, Radial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: URS1H010MDD1TD
Digikey Part Number: 493-11473-1-ND
Quantity in Assembly: 1

C22, C23 -47uF, 10V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1A470MAD
Digikey Part Number: 493-14808-ND
Quantity in Assembly: 2

C21, C53 - 10uF, 35V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1V100MAD
Digikey Part Number: 493-14419-ND
Quantity in Assembly: 2

High Loop PC Board

***17 Pin Header, Double Decker Boards ***

C20 - 10uF, 50V, 20%, Radial Lead, 85 deg
Replacement Manufacturer: Panasonic
Replacement Part Number: ECE-A1HKS100B
Digikey Part Number: P19588CT-ND
Quantity in Assembly: 1

C1, C39, C40, C41, C42, C43 - 10uF, 35V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1V100MAD
Digikey Part Number: 493-14419-ND
Quantity in Assembly: 6

C7 -47uF, 10V, 20%, Axial Lead, 85 deg
Replacement Manufacturer: Nichicon
Replacement Part Number: TVX1A470MAD
Digikey Part Number: 493-14808-ND
Quantity in Assembly: 1