

MASTR®II MAINTENANCE MANUAL

138-174 MHz, 110-WATT TRANSMITTER-MOBILE AND STATION (with Phase Lock Loop Exciter)




TABLE OF CONTENTS

SPECIFICATIONS	ii
DESCRIPTION AND MAINTENANCE	LBI30753 (DF3156)
EXCITER	LBI30398 (DF3165)
POWER AMPLIFIER	LBI30739 (DF3166)

SPECIFICATIONS*

Power Output 110 Watts (Adjustable from 22 to 110 Watts)

Crystal Multiplication Factor 12

Frequency Stability

5C-ICOM with EC-ICOM ±0.0005% 2C-ICOMS ±0.0002%

Spurious and Harmonic Emission At least 85 dB below full rated power output. (Per EIA RS-152-B, Para. 4)

Modulation Adjustable from 0 to ±5 kHz swing with instantaneous modulation limiting.

Audio Sensitivity 65 to 125 Millivolts (Mobile) 10 to 120 Millivolts (Station)

Audio Frequency Characteristics Within +1 dB to -3 dB of a 6-dB/octave pre-emphasis from 300 to 3000 Hz per EIA standards. Post limiter filter per FCC

and EIA.

Distortion Less than 3%

Deviation Symmetry 0.5 kHz maximum

 Maximum Frequency Spread

 138-155 MHz
 17 MHz

 148-174 MHz
 24 MHz

Duty Cycle EIA 20% Intermittent (Mobile and Stations)

Continuous (Stations)

RF Output Impedance 50 ohms

Temperature Range -40°C to $+70^{\circ}\text{C}$ (Mobile) -30°C to $+60^{\circ}\text{C}$ (Station)

* These Specifications are intended primarily for the use of the serviceman. Refer to the appropriate Specification Sheet for the complete specifications.

— WARNING —

Although the highest DC voltage supplied to the MASTR $^{\$}$ II transmitter is +12 Volts DC, high current may be drawn under short circuit conditions. These currents can possibly heat metal objects such as tools, rings, watchbands, etc., enough to cause burns. Be careful when working near energized circuits!

High-level RF energy in the transmitter Power Amplifier assembly can cause RF burns upon contact. KEEP AWAY FROM THESE CIRCUITS WHEN THE TRANSMITTER IS ENERGIZED!

GENERAL ELECTRIC COMPANY • MOBILE COMMUNICATIONS DIVISION WORLD HEADQUARTERS • LYNCHBURG, VIRGINIA 24502 U.S.A.

